

ONYX Series

LED Retrofit Downlight

Nora Lighting's new Onyx Series offers an economical quality solution to LED Retrofit Downlighting. Deep-set optics produce visual comfort in 4" and 5"/6" apertures. The Onyx produces 90+ CRI for true vibrant color rendition. Adjustable, baffle and reflector styles blend with popular trims and create an uniform ceiling appearance. The 4" 650 lumen/10 watt unit is compatible with Nora's dedicated housing to meet energy rebate requirements, as well as Nora's 4" medium base housings and 4" housings by others. The 5"/6" 750 lumen/ 12 watt unit is compatible with Nora's dedicated 5" and 6" housings to meet energy rebate requirements, as well as Nora's 5" and 6" medium base housings and 5" and 6" housings by others. cULus, Energy Star and Title 24 listed, the Onyx by Nora can be used in new construction, remodel and retrofit applications. Onyx is the smart choice for energy-efficient, dimmable lighting.



FEATURES

- 5 year limited warranty
- Deep set optics
- 90+ CRI
- 4" – 650 Lumen / 10 watt
- 5"/6" – 750 Lumen / 12 watt
- 2700K, 3000K and 4000K CCT
- Adjustable, Baffle and Reflector styles
- White Finish
- Dimmable
- Includes Medium Base socket for easy retrofitting
- Small disconnect compatible with most dedicated housing by others.
- 36,000 Hour Life
- Energy Star rated
- cULus listed for Wet location
- Title 24 Compliant / JA8 Compliant









ONYX SERIES 4" AND 5"/6" LED RETROFIT DOWNLIGHTS

ONYX SERIES 4", 5"/6" LED RECESSED RETROFIT

| SERIES | APERTURE | TRIM STYLE | COLOR TEMP | FINISH |
|--------------------|--------------------------|----------------------|-----------------|-----------------------------------|
| NOX- Onyx Retrofit | 4 4" Aperture | 31 Reflector | 27 2700K | WW White with White Flange |
| | 56 5"/6" Aperture | 32 Baffle | 30 3000K | |
| | | 34 Adjustable | 40 4000K | |

Example: **NOX-43430WW** - 4" Adjustable Onyx Series LED Retrofit unit, 3000K, White finish

COMPATIBLE NORA HOUSINGS

| NEW CONSTRUCTION | | REMODEL | |
|--|--------------------------------|------------------------|--------------------------------|
| NSIC-401QAT | 4" ICAT Line Voltage | NSR-404QAT | 4" AT Line Voltage |
| NS-401QAT | 4" AT Line Voltage | NHRIC-4G24AT | 4" ICAT GU24 |
| N HIC-4G24AT | 4" ICAT GU24 | NHRIC-4LMRAT* | 4" ICAT Dedicated LED |
| NHIC-4LMRAT* | 4" ICAT Dedicated LED | | |
| NHIC-4LMRAT/277* | 4" ICAT Dedicated LED, 277V | NHRIC-504QAT | 5" ICAT Line Voltage |
|  NFBIC-4INCAT | 4" ICAT Fire Box | NHR-504Q | 5" Line Voltage |
|  NFBIC-4LMRAT* | 4" ICAT Dedicated LED Fire Box | NHRIC-527QAT | 5" ICAT Shallow Line Voltage |
| | | NHRIC-5G24ATFL | 5" ICAT GU24 |
| NHIC-501QAT | 5" ICAT Line Voltage | NHRIC-5LMRAT* | 5" ICAT Dedicated LED |
| NH-501Q | 5" Line Voltage | NHRIC-527LMRAT* | 5" ICAT Shallow Dedicated LED |
| NHIC-5G24ATFL | 5" ICAT GU24 | | |
| NHIC-527QAT | 5" ICAT Shallow Line Voltage | NHRIC-17QAT | 6" ICAT Line Voltage |
| NHIC-5LMRAT* | 5" ICAT Dedicated LED | NHRIC-17QNBAT | 6" ICAT Line Volt (No Bracket) |
| NHIC-5LMRAT/277* | 5" ICAT Dedicated LED, 277V | NHRIC-27QAT | 6" ICAT Shallow Line Voltage |
| NHIC-527LMRAT* | 5" ICAT Shallow Dedicated LED | NHR-26Q | 6" Line Voltage |
|  NFBIC-5INCAT | 5" ICAT Fire Box | NHRIC-6G24ATFL | 6" ICAT GU24 |
|  NFBIC-5LMRAT* | 5" ICAT Dedicated LED Fire Box | NHRIC-6LMRAT* | 6" ICAT Dedicated LED |
| | | NHRIC-27LMRAT* | 6" ICAT Shallow Dedicated LED |
| NHIC-17QAT | 6" ICAT Line Voltage | | |
| NHIC-17QNBAT | 6" ICAT Line Volt (No Bracket) | | |
| NHIC-27QAT | 6" ICAT Shallow Line Voltage | | |
| NH-26Q | 6" Line Voltage | | |
| NH-26QNB | 6" Line Voltage (No Bracket) | | |
| NHIC-6G24ATFL | 6" ICAT GU24 | | |
| NHIC-6LMRAT* | 6" ICAT Dedicated LED | | |
| NHIC-6LMRAT/277* | 6" ICAT Dedicated LED, 277V | | |
| NHIC-27LMRAT* | 6" ICAT Shallow Dedicated LED | | |
|  NFBIC-6INCAT | 6" ICAT Fire Box | | |
|  NFBIC-6LMRAT* | 6" ICAT Dedicated LED Fire Box | | |

* Nora LED Dedicated housings are cULus listed for use only with Nora Diamond/Cobalt/Onyx Series LED Retrofits.

**Consult factory for EM options